


# IPLD-32x128-4-ODN

(Enclosed Outdoor)



## Wayside Sign

- ◆ Compact sign designed for close up viewing
- ◆ Angled design to be installed above eye level



## > Specifications

### ◆ Internals

LEDs: Array 32x128; 4096 pixels; full color, Dot Pitch of 4 MM  
Processor: ARM A8 at 1GHz; Memory: 1GB SDRAM; uSD Memory card: 2GB min..

### ◆ Electrical

Ethernet - RJ45 - 10/100Mb Cat5.  
USB 2.0 - Host - Type A connector.  
Audio - 3.5mm Stereo Jack - 3 conductor.  
Power Switch - DPDT 1/0 legend marked.  
Case: 2 -3/4" Knockout Opening.  
Power Connections: Wago Lever Nuts.

### ◆ Power Requirements

Input - 95 ~ 260VAC at 50 ~ 60Hz.  
Power Consumption:  
160W maximum  
40W typical

### ◆ Environmental

Operating Temperature:  
-34°C ~65°C ambient.  
-30°F ~ 150°F ambient.  
Relative Humidity:  
up to 90 % non-condensing.  
Ethernet Isolation:  
1500VAC min per IEEE 802.3.  
Enclosure:  
IP65 Rated LEDs - PTFE gasketed.

### ◆ Speaker Option Available

Speaker and audio files can be added

### ◆ Mechanicals

Length: 39"(990.6mm)  
Height: 14"(335.6mm)  
Depth: 4"(101.6mm)  
Weight: 20lbs est(9.07kg).

### ◆ Mounting Options

Side Brackets for wall mount option  
Threaded Inserts in top for hanging option



## > Display Features

### Direct PLC Interfaces

Connect to Standard based PLC's including: Ethernet/IP, Modbus/TCP, Melsec(Mistubishi), FINS (ORMAN), and OPC.

### Remote 'snapshot'

Not where you can see your display, no problem. View exactly what is on the display no matter where you are. The sign generates an instant copy of what is being displayed and sends it right to your browser.

### Integrated 10/100 Ethernet

This is the core of our technology which allows for superior ease of use and intergration in conjunction with the unit's built-in web-server. TCPIP enabled our of the box. Use built-in support for DHCP and NTP to aid in your ease of configuration



### Data thresholds

Set thresholds on your data to change your message color or state to bring impact to an event.

### Server-free solution

With easy web-based interfaces and easy to program XML data structures, no longer do you need middleware or any additional hardware to accumulate data saving you time, money and resources.

### Browser based interface

Ease of use exemplified. Manage your display from a simple web-browser anywhere - any time. Send messages, check status, and manage thresholds, layouts, remote or local data fields all from web pages Hosted on the sign. No software to install and not custom programming needed.

### Live message elements

Insert data into any messages. You can have real-time data and see it update dynamically on the display. Any message may contain static or scrolling text, live data, database elements., clocks, bit-mapped graphics or any combination therein.



### Dynamic sign layouts

Schedule any number of layouts with our Playlist manager. Show real-time data, statistics, company news, safety information, or general messages in their own unique layout to get the impact you want. The Playlilst manager allows you to schedule the times and order - it is all under your control.

### Fonts, graphics and effects

Use any of the 44 built-in text or graphics fonts to build your message. Add pizzazz using the built-in enter and exit effects.



### Conditions/Program Logic

Program logic can be tied to variable on the sign. As data is changed "Program Logic can be used to Activated/Deactivate Messages, Layouts, Thresholds, Commands or even update other variables on the sign.



### Simple Integration/Open Interface

Use simple standard XML syntax and constructs to send data to the display. No proprietary protocols, syntaxes, or languages to learn. Any XML capable application like MS Excel or SQL Server or programming languages like Perl, VB, or C# can easily update data fields or elements on the sign.

